



OTM-3550

FREQUENCY AGILE TELEVISION MODULATOR

Features / Benefits

- Any output channel from Ch.2 (55.35MHz) through Ch.ppp (547.25MHz)
- Available with remote control and sub-band output
- 60dB spurious free dynamic range
- Greater than 80dB out-of-band carrier to noise ratio
- BTSC stereo compatible
- Dual IF loops
- Saw IF filtering for the ultimate in adjacent channel performance
- Low power consumption for reliable long term operation
- Available in four standards - NTSC, PAL, B/G, PAL I and PAL D



The agile **OTM-3550** modulator is a full feature, SAW filtered unit that is available in four standards; NTSC, PAL B/G, PAL I and PAL D. The **OTM-3550** provides high level (+60dBmV) outputs on any channel from ch. 2 (55.25MHz) through ch. PPP (547.25MHz). Sub-Band output capabilities are offered as options. All channels are selectable by front panel DIP switches including F.C.C offsets. Features such as >80dB out-of-band C/N ratio; (which allows unlimited numbers of the **OTM-3550** to be combined without the need for external bandpass filters), BTSC stereo compatibility, along with low power consumption (14 watts typical) all combine to make the **OTM-3550** Series a modulator that offers not only high performance, but excellent reliability as well.

Available through

Multicom, Inc.

1076 Florida Central Parkway, Longwood, FL 32750

Ph: 407-331-7779 Toll Free: 800-423-2594 Fax: 407-339-0204

www.multicominc.com

multicom@multicominc.com

OTM-3550



SPECIFICATIONS

Output frequency range.....	54MHz (ch. 2) 547.25MHz (ch. PPP). Selectable in 1MHz increments
RF output level.....	+60dBmV typical, +55dBmV minimum
Frequency accuracy/stability.....	<±5KHz of selected channel frequency
Out-of-band C/N ratio.....	>80dB as measured in a 4.0MHz noise bandwidth
Spurious outputs.....	>60dB below output visual carrier level @ 55dBmV output
Dual IF loop output.....	Visual Carrier +40dBmV @ 45.75MHz Aural Carrier +20dBmV to +28dBmV @ 41.25MHz
Video carrier level.....	Adjustable downward by 10dB minimum
Video performance.....	Measured @ 80% modulation. Differential gain <6%. Differential phase <3°. Video input 1 volt p-p(75Ω)
Audio intercarrier stability.....	<±1KHz.
Audio deviation.....	25KHz – 75 msec pre-emphasis.
BTSC stereo/mono.....	Internal defeat of audio pre-emphasis for BTSC baseband input.
Audio/video ratio.....	Adjustable from 12dB to 20dB below video carrier.
Front panel controls.....	Channel/F.C.C. offset selectable by DIP switch. Video/Audio modulation, A/V ratio and R.F. level by pot adjustment.
Front panel indicators.....	LED's for video/audio overmodulation.
Rear panel connectors.....	Type F video input (75Ω input Z), RF output, -20dB test and video/audio i.f. loops. Audio input terminal strip (600Ω input Z). balanced. 3-wire power cord U.S.A. plug.
Power consumption.....	100-240 VAC @ 50/60Hz 13 watts.
Size.....	1.75" H x 19" W x 8" D.

MODEL OPTIONS

OTM-3550-SW	Same features as OTM-3550 but with sub-band output channels T-7 (7MHz) through channel PPP (547.25MHz) including all HRC/IRC channels. Selectable in 0.25 increments.
--------------------------	--

Available through

Multicom, Inc.

1076 Florida Central Parkway, Longwood, FL 32750

Ph: 407-331-7779 Toll Free: 800-423-2594 Fax: 407-339-0204

www.multicominc.com

multicom@multicominc.com