

# Cisco Model DPC3825 8x4 DOCSIS 3.0 Wireless Residential Gateway

The Cisco<sup>®</sup> Model DPC3825 8x4 DOCSIS 3.0 Wireless Residential Gateway (DPC3825) is a high-performance home gateway that combines a cable modem, router, and wireless access point in a single device providing a cost-effective voice and networking solution for both the home and small office. The DPC3825 provides a faster connection to the Internet by incorporating eight bonded downstream channels along with four bonded upstream channels. These bonded channels can deliver downstream data rates in excess of 340 Mbps and upstream data rates in excess of 120 Mbps. That's up to eight times faster downloads than conventional single-channel DOCSIS<sup>®</sup> 2.0 cable modems.

The DPC3825 is designed to meet DOCSIS 3.0 specifications, as well as offering backward compatibility for operation in DOCSIS 2.0, 1.1, and 1.0 networks.

Figure 1. Cisco Model DPC3825 8x4 DOCSIS 3.0 Wireless Residential Gateway (image may vary from actual product and specification)



Designed for the active digital home or office, the DPC3825 integrated router features a Dynamic Host Configuration Protocol (DHCP) server, Network Address and Port Translation (NAT/NAPT) and a Stateful Packet Inspection (SPI) firewall. These features allow the user to share a single high-speed public Internet connection as well as share files and folders between devices within the home network by attaching multiple wired and wireless devices in your home or office to the wireless residential gateway.

Consumer-friendly features such as Wireless Protected Setup (WPS) and user-configured Parental Control can protect the home network from unwelcome intruders and family members from access

Purchase from Multicom MULT

COM www.multicominc.com | 800-423-2594

### **Features**

#### DOCSIS

 Compliant with DOCSIS 3.0, 2.0, 1.1, and 1.0 standards to deliver high-end performance and reliability

#### Connections

- Four 10/100/1000BASE-T Ethernet ports to provide wired connectivity
- High-performance broadband Internet connectivity to energize your online experience
- 802.11n, Single Band 2.4 GHz 2x2 Wireless Access Point (WAP) with four Service Set Identifiers (SSIDs) or optional Dual-Band non-concurrent radio
- WPS, including a push-button switch to activate WPS for simplified and secure wireless setup
- USB host port

#### **Design and Function**

- Attractive, compact design and versatile orientation to stand vertically, lie flat on the desktop or shelf, or mount easily on a wall
- Dual color LED status indicators on the front-panel provide an informative and easy-tounderstand display that indicates the cable modem operational status
- TR-068 compliant color-coded interface ports and corresponding cables simplify installation and setup

#### Management

- User-configurable Parental Control blocks access to undesirable Internet sites
- · Advanced firewall technology deters hackers and protects the home network from unauthorized access
- Allows automatic software upgrades by your service provider

#### **Software and Documentation**

· CD-ROM containing user guide





Figure 2. Cisco Model DPC3825 Front Panel (image may vary from actual product and specification)

Table 1. Front Panel Features

Feature	Description
Indicators	Power, DS, US, Online, Ethernet, USB, Wireless Link, Wireless Setup
Color	Black, black lens, silver text
Branding	Cisco and model number

Figure 3. Cisco Model DPC3825 Back Panel (image may vary from actual product and specification)



Table 2. **Back Panel Features** 

Feature	Description
POWER Connector Color: Black	Connects the wireless home gateway to the DC output of the AC power adapter
POWER SWITCH (Not Shown)	Turns power ON and OFF (available only on products carrying the CE mark)
MAC ADDRESS LABEL	Displays the MAC address of the cable modem
USB Color: Blue	Type 2 USB 2.0 port connects to a USB port on select devices
ETHERNET (1 – 4) Connector Color: Yellow	Four RJ-45 Ethernet ports connect to the Ethernet port on your PC or your home network
CABLE Connector Color: White	F-connector connects to an active cable signal from your service provider
RESET	Power cycles the cable modem
WIRELESS SETUP	Activates WPS, which allows you to add wireless devices to the wireless network of the residential gateway
ANTENNA (internal)	(2) internal antennas provide a communication connection for the built-in 802.11n wireless



### Data Sheet

# **Product Specifications**

#### Table 3. Product Specifications

Specification	Value		
Residential Gateway			
Gateway Configuration	TR-069 and subset of TR-098 data model (optional)		
Management	Extensive custom SNMP MIB for the Gateway		
	<ul> <li>Provisioning with XML and/or with SNMP</li> </ul>		
	HNAP server 1.2+		
ICSA (Independent	Web filtering: Pop-ups, Cookies, Java & ActiveX scripts		
Computer Security Association) Firewall	Intrusion detection/prevention: WAN ping blocking, IP fragment blocking, Port scan		
Compliant	detection, TCP Port Probe, UDP Port Probe		
	<ul> <li>DoS Protection: inbound, outbound, WAN interface, LAN interface, SYN flood, Ping of Death, Smurf, Bonk, Jolt, Land, Nestea, Newtear, Syndrop, Teardrop, WinNuke/OOBNuk</li> </ul>		
	(Invalid TCP urgent pointer), x1234, Saihyousen , Oshare, ARP flood, TCP Hijacking,		
	Christmas Tree, SYN/FIN (jackal), BackOffice (UDP 32337), NetBus, ICMP Flowding,		
	IP Address, Port Number, MAC address filtering		
	TCP flags, ICMP types fragmentation		
	Connection Creation and Teardown		
	Timestamps and Payload Modification		
Parental Controls	Per-User Policies		
	Keyword blocking		
	Domain name blocking		
	• Time of day filters		
	MAC Address Filtering		
Advanced Event Logging	Filtering Activity		
	Session Tracking		
	User Notification via E-mail Alert and SNMP Traps		
Routing Features	<ul> <li>NAPT, NAT, and Pass-through (layer 2) Operational Modes</li> </ul>		
	<ul> <li>RFC3489 (STUN) "Port-restricted cone NAT" behavior</li> </ul>		
	• RIP v1/v2, with MD5		
	Static Routes		
	Port Forwarding		
	Port Triggering		
	UPnP IGD 1.0		
	IPSec Pass-through     A DTD Data through		
	L2TP Pass-through		
	<ul> <li>PPTP Pass-through</li> <li>ALG support: mIRC, PIRCH, MS NetMeeting, Net2phone, AOL and MSN Messenger,</li> </ul>		
	Yahoo Messenger, Go2Call, Hotline Server, Visual IRC, CuSeeme, AT&T Instant,		
	Messenger Anywhere, Active Worlds, Buddy Phone Calista IP Phone, Delta Three PC to		
	Phone, Dial Pad, Dwyco Video Conferencing, OrbitRC, Xircon, Netscape Chat, FTP, H.323, ICQ		
Wireless Access Point	1		
802.11 b/g/n	• 2x2 2.4 GHz or optional 2x2 2.4 GHz/5 GHz Dual-Band, non-concurrent, wireless access		
J.	point		
	(2) Internal Antennas		
	<ul> <li>Wi-Fi Compliant Security (WPA2-Enterprise, WPA2-PSK, WPA-Enterprise, WPA-PSK, WEP)</li> </ul>		
	WMM-QoS (Wireless Multi Media - Quality of Service)		
	WMM Power Save		
	• WPS		
	• Wireless Bridging - WDS (Wireless Distribution System) – allows connection to "Range		
	<ul> <li>Extender Products"</li> <li>RADIUS Authentication (Client, EAP-TLS, EAP-TTLS, EAP-PEAP, EAP-MD5)</li> </ul>		
	<ul> <li>RADIUS Authentication (Client, EAP-TLS, EAP-TLS, EAP-PEAP, EAP-MD5)</li> <li>MBSSID (4 SSIDs with unique NAT scopes)</li> </ul>		
	WiFi "Hot Spot" support (Static DHCP IP Scope over tunnel)		
	- WELL HOLSPOL Support (Static DHOF IF Scope over tunner)		

Specification	Value				
RF Downstream					
Operating Frequency Range	88 to 1002 MHz				
Tuner Frequency Range	88 to 1002 MHz				
Tuner	(2) Frequency agile block tuners, 32 MHz bandpass each				
Demodulation	8 demodulators, 4 per tuner, each demodulator; 64 QAM or 256 QAM				
Maximum Data Rate	8 downstream channels, each 6 MHz channel: 42.88 Mbps for 256 QAM and 30.34 Mbps for 64 QAM				
Bandwidth	6 or 8 MHz				
Operating Level Range	-15 to +15 dBm\	/			
Input Impedance	75 ohms				
RF Upstream	<u> </u>				
Operating Frequency Range	5 to 42 MHz, 5 to	o 65 MHz or 5 to 85 MHz	2		
Transmitter Frequency Range	5 to 42 MHz, 5 to 65 MHz or 5 to 85 MHz				
Upstream Transmission	4 upstream char	inels			_
Modulation	QPSK, 8 QAM, 1	16 QAM, 32 QAM, 64 QA	M / ATDMA, 12	8 QAM / SCDMA	
Maximum Data Rate per channel	Modulation	Channel Bandwidth (MHz)	Raw <u>Data Rate (</u>	Mbps)	
	QPSK	1.6	2.56		
	16 QAM	1.6	5.12		
	QPSK	3.2	5.12		
	16 QAM	3.2	10.2		
	32 QAM	3.2	12.8		
	64 QAM	3.2	15.4		
	16 QAM	6.4	20.5		
	32 QAM	6.4	25.6		
	64 QAM	6.4	30.7		
Bandwidth	200 kHz to 6.4 M	1Hz			
Maximum Operating Level	Modulation	One Channel	2 Channels	3 or 4 Channels	
TDMA	QPSK	+61 dBmV	+58 dBmV	+55 dBmV	
	8 QAM	+58 dBmV	+55 dBmV	+52 dBmV	
	16 QAM	+58 dBmV	+55 dBmV	+52 dBmV	
	32 QAM	+57 dBmV	+54 dBmV	+51 dBmV	
	64 QAM	+57 dBmV	+54 dBmV	+51 dBmV	
SCDMA	QPSK	+56 dBmV	+53 dBmV	+53 dBmV	
	8 QAM	+56 dBmV	+53 dBmV	+53 dBmV	
	16 QAM	+56 dBmV	+53 dBmV	+53 dBmV	
	32 QAM	+56 dBmV	+53 dBmV	+53 dBmV	
	64 QAM	+56 dBmV	+53 dBmV	+53 dBmV	
	128 QAM	+56 dBmV	+53 dBmV	+53 dBmV	
Electrical					
Input Voltage	15 VDC				
Power Consumption (DC)	~12 Watts				
Data Ports	GigE (Auto-negotiate with Auto-MDIX): RJ-45 Ethernet (4) USB 2.0: USB Type 2 (1)				
RF	Female F-Type				
	7,5-5				

Specification	Value		
Mechanical			
Dimensions (W x D x H)	Not including F-Type connector:		
	5.7 in. x 6.9 in. x 1.8 in. (14.5 cm x 17.6 cm x 4.5 cm)		
Weight	13.76 oz. (0.390 kg)		
Operating Temperature	32° to 104°F (-0° to 40°C)		
Operating Humidity	0 to 95% RH non-condensing		
Storage Temperature	-4° to 158°F (-20° to 70°C)		
Standards and Approvals			
Designed to meet with the	DOCSIS 3.0, 2.0, 1.1, and 1.0		
following standards	IEEE 802.11 b/g/n		
	WEP, WPA, and WPA2		
	WMM, WPS		
Regulatory Compliance			
Regulatory and Safety Approvals	As required per country where the DPC3825 will be used		

# **Ordering Information**

#### Table 4. Ordering Information

Description	Part Number
5-42/88-1002 MHz Diplex Filter	
8 MB Flash X 64 MB DRAM Memory Configuration (Standard Configuration)	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4034138
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, North America (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
North America	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4038277
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
Power cord, North America (non-polarized)	
Ethernet cable	
CD-ROM containing user guide	
North America (Customer-specific configuration)	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4038465
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, North America (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
North America (Customer-specific configuration)	



Description	Part Number
5-42/88-1002 MHz Diplex Filter	
8 MB Flash X 64 MB DRAM Memory Configuration (Standard Configuration)	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4037054
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, North America (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
North America (Customer-specific configuration)	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4037934
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, Europe (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
Europe	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4037652
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, Argentina (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
Argentina	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4039447
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
Power cord, Brazil (non-polarized)	
Ethernet cable	
CD-ROM containing user guide	
Brazil	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4039151
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
Power cord, North America (non-polarized)	
Ethernet cable	
CD-ROM containing user guide	
Columbia (Customer-specific configuration)	



Description	Part Number
5-65/88-1002 MHz Diplex Filter	
32 MB Flash x 128 MB DRAM Memory Configuration	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4039640
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, North America (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
North America	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4039759
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching regulated-power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, North America (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
North America (Customer-specific configuration)	
5-65/88-1002 MHz Diplex Filter	
8 MB Flash x 64 MB DRAM Memory Configuration (Standard Configuration)	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4034139
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop switching-regulated power supply with detachable power cord</li> </ul>	
<ul> <li>Power cord, Japan (non-polarized)</li> </ul>	
Ethernet cable	
CD-ROM containing user guide	
Japan (Customer-specific configuration)	
DPC3825 DOCSIS 3.0 8x4 Wireless Residential Gateway includes:	4034140
802.11n 2x2 Wireless Access Point	
USB 2.0 host port	
<ul> <li>100-240 VAC / 50-60 Hz, 15 VDC/ 1 A Desktop style switching regulated-power supply with detachable power cord</li> </ul>	
• Power cord, Japan (non-polarized)	
Ethernet cable	
A OD DOM containing ware suids	
CD-ROM containing user guide	





# **Replacement Components**

Table 5.	Replacement Components
----------	------------------------

Description	Part Number
Power Supply	
Class 2 Switching Regulated	
100-240 VAC/50-60 Hz, 15 VDC / 1.5 A desktop-style switching regulated power supply with detachable power cord (order power cord separately)	4034524
Power Cord	
Power cord, 2 conductors, NEMA 1-15 to C7, North America (polarized)	4026134
Power cord, 2 conductors, Argentina (non-polarized)	4012938
Power cord, 2 conductors, CEE7/16 to C7, INMETRO, Brazil (non-polarized)	4009115
Power cord, 2 conductors, CEE7/16 to C7, Europe (non-polarized)	503414
Data Cable	
Ethernet cable, 1.2 meters	740580
Ethernet cable, 2.0 meters	4018790
CD-ROM	·
CD-ROM with user guides and USB driver	4034136

