



# Multicom® TotalGUARDIAN® MTG-GIR32

## Product Specifications

### Description

Expand your TotalGUARDIAN MTG-EL24 system to accommodate any size headend - from the smallest to the largest - with the Multicom MTG-GIR32 Expansion Unit.

### Key Features - All Standard

- Expands the TotalGUARDIAN MTG-EL24 by an additional 32 IR ports allowing you to connect 32 additional devices
- Up to 48 MTG-GIR32 can be connected to a single MTG-EL24 system giving you remote control access to more than 1,500 devices
- Simple connection to the MTG-EL24 via Ethernet port




Specifications		Values	Notes
Ports	IR	32	With 1/8" connector Includes 32 Blaster Cables with LED Indicators
	Ethernet Port	1	Must be connected to MTG-EL24
Front Panel	LCD Display	2 Lines - 32 Characters	
	Status Indicator	LED	Green/Red/Blue
	Reset/Configuration	1	Recessed button
General	Satellite Receiver Capability	DISH VIP222(K), 211(K), 311, 322, 2800 - Ask about other compatible equipment	Expansion units (MTG-GIR32) allow for virtually unlimited number of receivers
	Remote Control and Monitoring	Any device with Internet connectivity	
	Operating temp. (°C)	0 - 50	32 - 122°F
	Storage temp. (°C)	-40 - 85	-40 - 185°F
	Operating relative humidity (%)	5 - 95	Non-condensing
	Power Supply	120VAC	
	Power Consumption	15W .13Amp	
Size (W x D x H inches)	19 x 9.25 x 1.75	1RU	

### TotalGUARDIAN Product Series

Part #	Function	Capacity per Unit	Max Units
MTG-GIR32	Expansion Unit	32 IR Ports	48
MTG-EL24	Headend Server	24 IR Ports	1
MTG-GPDU	Power Distribution Unit	8 - 120VAC Power Outlets, 15 Amp	99

Remote Control of All Your Headends is in the Palm of Your Hand



[www.multicominc.com](http://www.multicominc.com)

Multicom, Inc.  
Ph: 800-423-2594  
Fax: 407-339-0204

Email: [multicom@multicominc.com](mailto:multicom@multicominc.com)